

ELIT EST-68

Strømtang stor

Lækage strømtang Ø68mm til Euromaster AutoEv. Måler fra 1mA til 100AAC KAT III 600V.

Teknisk beskrivelse

ELIT EST-68 er en robust strømtang, der er velegnet til måling af både lækstrøm og belastningsstrøm. Måler fra 1mA til 100A AC, når den er tilsluttet EuroMaster AutoEv. Det er muligt at logge strøm på AutoEv under måling, hvilket gør EST-68 velegnet til lokalisering af periodiske fejlstrømme. 4 mm tilslutninger. Sikkerhedskategori KAT IV 600V

Fordele:

Opretter forbindelse til Euromaster AutoEV til måling og logning af strøm
Måleområde fra 1mA til 100AAC

Stor strømtang til både belastningsstrømme og lækstrømme med 4 mm bananstik for tilslutning til instrumentet.



Produkt navn/ Art.nr/ El. nummer/ GTIN	ELIT EST-68/ 8011347/ 1130155/ 7070811212377
Ifølge:	---
Analogue bar graph display	No
Current measuring range, AC	0 - 100
True RMS measurement	Yes
Voltage measurement, AC	No
Voltage measurement, DC	No
Resistance measuring range	No
Power measuring	No
Leakage current measuring	Yes
Top arbour measurement	Yes
Measurement in cables with for- and back conductor	No
Jaw opening	68
Version as adapter to connect to multi meter	Yes
Interface	No
Continuity test	No