



# ELIT Pri-Watt 3-fase

Residential kitchen wattmeter 0-15kW 3-phase

## Technical description

Without you realizing it, equipment may be on that shouldn't have been on. This is where this small instrument that can be mounted in a standard wall box or in a wall-mounted box comes in. This gives you a continuous overview of how much power is on in your house. By, for example, mounting this in the hallway by the front door, you always have the assurance that no more equipment is on than was intended. A red indicator can be set to normal consumption so that you can easily compare. Have I turned off the heating cables? Max 15kW. Max 65AAC, 230VAC. Contents: Instrument and transformer. Hole diameter in transformer is 12mm. Size of transformer (WxHxD) is 122x45x44mm.

## Advantages:

Visualizes instantaneous value of power

Easy to install in standard wall box

Simple analog reading and with red adjustable pointer



Product name/ Art.nr/ GTIN	ELIT Pri-Watt 3-fase 0-15kW/ 20850000/ 7070810005567
According to:	---
Unit of measurement	Watt
Initial value scale	0
Nominal end value of the scale	15000
Width meter scale	70 Millimetre
Height meter scale	70 Millimetre
Max. needle deflection	100 Degrees
Mounting method	Built-in